

90+ LIGHTING



MODEL	RETROFIT DOWNLIGHT 15W 5" to 6" 1100LM 2700K E26
SKU	SE-350.063

DIMMER COMPATIBILITY LIST					
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY		
LUTRON	DIVA	DVCL-153P	OK		
		DVELV-300P	OK		
		DVELV-303P-AL	OK		
		DVELC-303P-WH	OK		
		DV-600P-WH	OK		
		DVELV-300P-WH	OK		
		603P-WH	OK		
		DVSCCL-153P	OK		
		DVWCL-153PH	OK		
		DVWCL-153PH-WH	OK		
		MAELV-600	OK		
		MAELV-600-WH	OK		
		MAELV-153M	OK		
		MAELV-153M-WH	OK		
		MAELV-300P	OK		
	DIVA C*L	MAESTRO	MRF2-3LD	OK	
			SELV-300P	OK	
			CTELV-303P	OK	
			S-600P	OK	
			CTCL-153P	OK	
			SELV-300P-WH	NC	
			SLV-600-WH	OK	
			S-603P-WH	OK	
			SLV-600P	OK	
			S-600P-WH	OK	
	MAESTRO WIRELESS	SKYLARK	LGCL-153P	OK	
			LGCL-153PL	OK	
			LGCL-153PLH-WH	OK	
			1B3211	OK	
			1C1311	OK	
			VIVE	MRF2S-6CL-WH	OK
			CASETA	PD-6WCL-WH	OK
			SPACER	SPSELV-600M	OK
			NOVA T	NTELV-300-WH	OK
				NTLV-600-277-WH	OK
	LUMEA	-	RRD-6CL-WH	OK	
			RRD-6CL	OK	
			RRD-6NA	OK	
			ARIADNI	AYCL-153P-WH	OK
			VIERTI	VTELV-600M	OK
			-	DVWCL-153PH/jsb1-85	OK
			-	NTLV-600-WH/jsb1-88	OK
			NOVA	NTLV-600-WH	OK
			TOGLER	TG-600PR	OK
			GRAFIK EYE QS	OSGRJ-6P	OK
INOVAT			NTELV-300	OK	
CASSETA			PD-6WCL	OK	
-			MRF2-3LDH	OK	
-			MAELV-153M-WH	OK	
-			SCL-153P-WH	OK	
-	DVELV-300P-WH	OK			
LEVITON	-	6674	OK		
		6633-P	OK		
		52136	OK		
		DECORA	R62-6674-POW	OK	
		-	V47-C06579	OK	
		-	6161	OK	
		-	RPI06-1/jsb1-103	OK	
		-	1PL06/jsb-92	OK	
		-	RTD01-10Z/jsb-100	OK	
		-	IPI06	OK	
		-	1PL06	OK	
		-	RTD01-10Z	OK	
		-	L20-6602	OK	
		MAXXIMA	-	DMB01/6	OK
		-	-	DMA02	OK
FEIT	-	LGCL-153PLH-WH	OK		
	-	LUTRO-S-600P-WH	OK		
	-	LEVITON-C20-06681-12A	OK		

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.