90+LIGHTING



MODEL	MR16 6W 500LM 3000K GU10 15D
SKU	SE-350.186

BRAND	DIMMER MODEL	COMPATIBILITY
MAESTRO	MRF2S-6CL-WH	OK
Caseta	PD-6WCL-WH	OK
DIVA	DV-600P-WH	OK
		OK
DIVA C*L	DVWCL-153PH-WH	OK
MAESTRO	MACL-153M-WH	OK
		OK
Skylark	S-603P-WH	OK
	SCL-153P-WH	NC
	SELV-300P-WH	OK
	SLV-600-WH	OK
Spacer	SPSELV-600M	OK
NOVA T	NTELV-300-WH	OK
	NTLV-600-277-WH	OK
Radio RA2	RRD-6CL-WH	OK
Ariadni	AYCL-153P-WH	NC
-	DIVA DVCL-153P	OK
-	MAELV-600	OK
-	SYLNRK SELV-300P	OK
-	SYLNRK CTELV-303P	OK
-	DIVA DVELV-300P	OK
-	DIVA DVELV-303P-AL	OK
-	Radio RA2 RRD-6NA	OK
-	DIVA DVELC-303P-WH	OK
-		OK
		OK
		OK
		OK OK
-		OK
-		OK
		OK
-		OK
		OK
-		OK
		OK
		OK OK
		OK OK
		OK
		OK OK
		OK OK
		OK OK
		OK OK
-	LEVITON - C20 - 06681 - 12A	OK OK
<u> </u>	MAESTRO Caseta DIVA DIVA C*L MAESTRO Skylark Spacer NOVA T Radio RA2 Ariadni	MAESTRO

DIMMER COMPATIBILITY

OK	Dims to < 15%	
OK	Dims to 15 - 30%	
NC	Not Compatible	

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 2) The results may be different for each application depending on the installation conditions.
 3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.

- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.

For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

