

90+ LIGHTING



MODEL	ST19 7W 600LM 2200K E26
SKU	SE-RCL06.1107-B

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DV-603P	OK	
		DVW-600PH-WH	NC	
		DV-603PH-WH	OK	
		DVCL-153PH	NC	
		DVCL-153P-WH	OK	
		DVWCL-153PH-WHC	OK	
		DV-600P-WH	NC	
		DVCL-253PH	NC	
		DVCL-153P-WH	OK	
		DVELV-300P-WH	OK	
	-	S-600	NC	
	-	D-600PH-DK	NC	
	-	DV-603PR	OK	
	-	S-600PR-WH	OK	
	SKYLARK	S-603PGH-WH	NC	
		S-10PH	NC	
		CTCL-153P-WH	OK	
		SCL-153P-WH	NC	
		S-600-IV	OK	
		S-600-AL	OK	
		S-603PH-WH	OK	
		S-600H-WH	NC	
		SCL-153PH-WH	OK	
		S-603P-WH	OK	
		SELV-300P-WH	OK	
		SLV-600-WH	OK	
		-	D-600RH-DK	NC
		TOGGLER	TG-600PH-WH	OK
			TG-600PH-IV	NC
	TGCL-153PH-WH		OK	
	MAW-600H-AL		NC	
	MAELV-600-WH		OK	
	MAESTRO	MAELV-600	NC	
		MAELV-600-WH	OK	
		MAELV-600	NC	
		D-600R-WH	OK	
		D-600R-IV	NC	
		DVCL-153P-WH-3	OK	
		AYCL-153P-WH	OK	
		AY-600PH-WH	NC	
		AYCL-153PH	OK	
		CT-103P-WH	OK	
	S-600P-WH	OK		
	ARIADNI	TG-600PNLH-WH	OK	
		LECL-153PH-WH	OK	
		MAELV-600-WH	OK	
		VIVE	OK	
		MRF2S-6CL-WH	OK	
	CASETA	PD-6WCL-WH	OK	
	SPACER	SPSELV-600M	OK	
NOVA T	NTELV-300-WH	OK		
NOVA T	NTLV-600-277-WH	OK		
RADIO RA2	RRD-6CL-WH	OK		
LEVITON	-	6684	NC	
	-	NO.6683	NC	
	-	6631-LA	OK	
	-	IPI06	NC	
	-	S-600P-WH	OK	
	-	NO.6672	OK	
	-	603-6631-A	OK	
	-	6631-A	OK	
	-	NO.IPL06	NC	
	-	IPI10-1LZ	NC	
	-	6683-10Z	NC	
	-	IPI06-1LZ	OK	
	-	NO.6631	OK	
	-	6681	NC	
	DECORA	R62-6674-POW	OK	
GE	18024	OK		
ALMOND	LUXDM600-12	OK		
CTL	DM600-12-3	OK		
AH	SDM3/1000	OK		
LEGRAND	SDM/600	NC		
	HCL453PTC	NC		
	DAL06P-C2-K	NC		
COOPER	TAL06P-C2-K	NC		
	SAL06P-W-K	NC		
	AAL06-C1	NC		
MAXXIMA	MEW-DM600	OK		
CTL	DM600-12-3/LED/WH	OK		
ADORNE	ADPD453LW2	OK		
ADORNE	ADWR703HW4	OK		
EATON	TAL06P1-C5	OK		

DIMMER COMPATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 - 2) The results may be different for each application depending on the installation conditions.
 - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.