

# 90+ LIGHTING



MODEL	BR40 13W 1000LM 2700K E26
SKU	SE-RCU03.1113

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DV-603P	NC	
		DVWCL-153PH-WH	OK	
		DVW-600PH-WH	OK	
		DV-600PH-WH	NC	
		DVCL-153PH	NC	
		DV-603PH-WH	NC	
		DVCL-153P-WH	OK	
		DVWCL-153PH-WHC	OK	
		DV-600P-WH	NC	
		DVCL-253PH	NC	
		DVELV-300P-WH	OK	
		S-600	NC	
		SKYLARK	CTCL-153P-WH	OK
			S-600PR-WH	NC
	S-603PGH-WH		NC	
	S-600H-WH		NC	
	S-10PH		OK	
	SCL-153P-WH		NC	
	S-600-IV		NC	
	S-600-AL		NC	
	S-603PH-WH		OK	
	S-600P-WH		NC	
	SCL-153PH-WH		OK	
	SELV-300P-WH		OK	
	SLV-600-WH		OK	
	S-603P-WH		OK	
	MAESTRO	D-600PH-DK	NC	
		MAW-600	NC	
		MAW-600H-AL	NC	
		MACL-153M-WH	NC	
		MACL-153MR-WH	NC	
		MACL-153MH-WH	NC	
		MSCL-OP153MH-WH	NC	
		MACL-153MLH-WH	NC	
		TG-603PGH-WH	NC	
		MAELV-600-WH	OK	
		DV-603PR	NC	
		D-600RH-DK	NC	
		TG-600PH-WH	OK	
		TG-600PH-IV	NC	
	TGCL-153PH-WH	OK		
	TOGLER	D-600R-WH	NC	
		D-600R-IV	NC	
		AYCL-153P-WH	OK	
		AY-600PH-WH	NC	
		AYCL-153PH	OK	
		MRF2S-6CL-WH	NC	
		PD-6WCL-WH	OK	
		SPSELV-600M	OK	
		NTELV-300-WH	OK	
NTLV-600-277-WH		OK		
RADIO RA2		NC		
RRD-6CL-WH		NC		
DECORA		R62-6674-POW	OK	
LEVITON		-	6684	NC
	-	NO.6683	OK	
	-	6631-LA	OK	
	-	IPI06	NC	
	-	S-600P-WH	NC	
	-	NO.6672	NC	
	-	603-6631-A	NC	
	-	6631-A	OK	
	-	NO.IPL06	OK	
	-	IPI10-1LZ	OK	
	-	6683-10Z	OK	
	-	IPI06-1LZ	OK	
	-	NO.6631	OK	
	-	6681	NC	
GE	18024	OK		
ALMOND	LUXDM600-12	OK		
CTL	DM600-12-3	OK		
AH	SDM3/1000	OK		
	SDM/600	OK		
LEGRAND	HCL453PTC	NC		
COOPER	-	DAL06P-C2-K	NC	
	-	TAL06P-C2-K	NC	
	-	SAL06P-W-K	NC	
	-	AAL06-C1	NC	
MAXXIMA	-	MEW-DM600	OK	

### DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

### 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
  - 2) The results may be different for each application depending on the installation conditions.
  - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
  - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.