

90+ LIGHTING



MODEL	PAR30 12W 850LM 2700K E26
SKU	SE-RL6.CE11.1412G

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DV-603P	OK	
		DVWCL-153PH-WH	OK	
		DVW-600PH-WH	NC	
		DV-603PH-WH	OK	
		DV-600PH-WH	NC	
		DVCL-153PH	NC	
		DVCL-153P-WH	OK	
		DVWCL-153PH-WHC	OK	
		DV-600P-WH	NC	
		DVCL-253PH	NC	
		DVELV-300P-WH	OK	
		-	S-600	OK
		SKYLARK	CTCL-153P-WH	OK
			S-600PR-WH	NC
	S-603PGH-WH		NC	
	S-600H-WH		OK	
	S-10PH		NC	
	SCL-153P-WH		NC	
	S-600-IV		NC	
	S-600-AL		OK	
	S-603PH-WH		OK	
	S-600P-WH		NC	
	SCL-153PH-WH		OK	
	S-603P-WH		OK	
	SELV-300P-WH		OK	
	SLV-600-WH		OK	
	D-600PH-DK		NC	
	-		MAW-600	NC
	MAESTRO	MAW-600H-AL	NC	
		MACL-153M-WH	NC	
		MACL-153MR-WH	NC	
		MACL-153MH-WH	NC	
		MSCL-OP153MH-WH	NC	
		MACL-153MLH-WH	NC	
		TG-603PGH-WH	NC	
		MAELV-600-WH	OK	
		-	DV-603PR	NC
		-	D-600RH-DK	OK
	TOGGLER	TG-600PH-WH	NC	
		TG-600PH-IV	OK	
		TGCL-153PH-WH	OK	
		-	D-600R-WH	OK
	-	D-600R-IV	OK	
	ARIADNI	AYCL-153P-WH	OK	
		AY-600PH-WH	NC	
		AYCL-153PH	OK	
		MRF2S-6CL-WH	OK	
	CASETA	PD-6WCL-WH	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
NTLV-600-277-WH		OK		
RADIO RA2	RRD-6CL-WH	OK		
LEVITON	DECORA	R62-6674-P0W	OK	
	-	6684	NC	
	-	NO.6683	NC	
	-	6631-LA	OK	
	-	IPI06	NC	
	-	S-600P-WH	OK	
	-	NO.6672	NC	
	-	603-6631-A	OK	
	-	6631-A	OK	
	-	NO.IPL06	NC	
	-	IPI10-1LZ	NC	
	-	6683-10Z	NC	
	-	IPI06-1LZ	NC	
	-	NO.6631	OK	
	-	6681	NC	
	-	S-600P-WH	OK	
	GE	18024	NC	
	ALMOND	LUXDM600-12	NC	
	CTL	DM600-12-3	OK	
	AH	SDM3/1000	OK	
SDM/600		OK		
LEGRAND	HCL453PTC	NC		
	DAL06P-C2-K	NC		
COOPER	TAL06P-C2-K	NC		
	SAL06P-W-K	NC		
	AAL06-C1	NC		
MAXXIMA	MEW-DM600	OK		

DIMMER COMPATIBILITY

OK
OK
NC

Dims to < 15%
 Dims to 15 - 30%
 Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
 For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.