

90+ LIGHTING



MODEL	PAR20 5.5W 500LM 2700K E26
SKU	SE-350.181

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DV-603P	OK	
		DVW-600PH-WH	NC	
		DV-603PH-WH	OK	
		DV-600PH-WH	OK	
		DVCL-153PH	NC	
		DV-603PH-WH	OK	
		DVCL-153P-WH	OK	
		DV-600P-WH	NC	
		DVWCL-153PH-WHC	OK	
		DVCL-253PH	NC	
		DVCL-153P-WH	OK	
		DVELV-300P-WH	OK	
		DVWCL-153PH-WH	OK	
		-	S-600	NC
		-	CTCL-153P-WH	OK
	SKYLARK	S-600PR-WH	OK	
		S-603PGH-WH	NC	
		S-600H-WH	NC	
		S-10PH	NC	
		SCL-153P-WH	NC	
		S-600-IV	OK	
		S-600-AL	OK	
		S-603PH-WH	OK	
		S-600P-WH	NC	
		SCL-153PH-WH	OK	
		S-603P-WH	OK	
		SELV-300P-WH	OK	
		SLV-600-WH	OK	
		-	D-600PH-DK	NC
		MAESTRO	MAW-600	NC
	MAW-600H-AL		NC	
	MACL-153M-WH		NC	
	MACL-153MR-WH		NC	
	MACL-153MH-WH		NC	
	MSCL-OP153MH-WH		NC	
	MACL-153MLH-WH		NC	
	TG-603PGH-WH		NC	
	MAELV-600-WH		OK	
	-		DV-603PR	OK
	TOGGLER	D-600RH-DK	NC	
		TG-600PH-WH	OK	
		TG-600PH-IV	NC	
		TGCL-153PH-WH	OK	
	-	D-600R-WH	OK	
	-	D-600R-IV	NC	
	ARIADNI	AYCL-153P-WH	OK	
		AY-600PH-WH	NC	
		AYCL-153PH	OK	
	VIVE	MRF25-6CL-WH	OK	
	CASETA	PD-6WCL-WH	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
	-	NTLV-600-277-WH	OK	
	RADIO RA2	RRD-6CL-WH	OK	
	DECORA	R62-6674-POW	OK	
	LEVITON	-	6684	NC
		-	NO.6683	NC
		-	6631-LA	OK
		-	IPI06	NC
		-	S-600P-WH	OK
-		NO.6672	OK	
-		603-6631-A	OK	
-		6631-A	OK	
-		NO.IPL06	NC	
-		IPI10-1LZ	NC	
-		6683-10Z	NC	
-		IPI06-1LZ	OK	
-		NO.6631	OK	
-		6681	NC	
-		S-600P-WH	OK	
-		18024	OK	
GE		-	LUXDM600-12	OK
ALMOND		-	DM600-12-3	OK
CTL		-	SDM3/1000	OK
AH		-	SDM/600	NC
LEGRAND	-	HCL453PTC	NC	
COOPER	-	DAL06P-C2-K	NC	
	-	TAL06P-C2-K	NC	
	-	SAL06P-W-K	NC	
MAXXIMA	-	AAL06-C1	NC	
	-	MEW-DM600	OK	

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 - 2) The results may be different for each application depending on the installation conditions.
 - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.