# 90+ LIGHTING

| | |
|---|---|
| **MODEL** | **PAR38 12W 1050LM 2700K E26** |
| **SKU** | **SE-350.179** |

## DIMMER COMPATIBILITY LIST

| MANUFACTURER | BRAND | DIMMER MODEL | COMPATIBILITY |
|---|---|---|---|
| LUTRON | DIVA | DVWCL-153PH-WH | OK |
| | | DV-600P-WH | OK |
| | | DVCL-153P-WH | OK |
| | | LUTRON DVCL-153P-WH | OK |
| | | DVELV-300P-WH | OK |
| | SKYLARK | CTCL-153PDH-WH | OK |
| | | SCL-153PH-WH | OK |
| | | S-603P-WH | OK |
| | | SELV-300P-WH | OK |
| | | SLV-600P-WH | NC |
| | | SLV-600-WH | OK |
| | MAESTRO | MACL-153M-WH | OK |
| | | MACL-153MH-WH | OK |
| | | MRF2S-6ND-120-SW | NC |
| | | MRF2S-6ND-120-WH | NC |
| | | MAELV-600-WH | OK |
| | TOGGLER | TGCL-153PH-WH | NC |
| | ARIADNI | AYCL-153P-WH | OK |
| | VIVE | MRF2S-6CL-WH | OK |
| | CASETA | PD-6WCL-WH | OK |
| | SPACER | SPSELV-600M | OK |
| | NOVA T | NTELV-300-WH | OK |
| | | NTLV-600-277-WH | OK |
| | RADIO RA2 | RRD-6CL-WH | OK |
| | - | NLV-1000-LA | OK |
| | - | P-PKG1W-WH | OK |
| LEVITON | DECORA | R62-6674-P0W | OK |
| | - | NO.6672 | OK |
| | - | WHITE NO.IPL06 600W | OK |
| | | IPL06-011-10Z | OK |
| | - | DW6HD-1BZ | OK |
| | - | DDL06-010-BLZ | OK |
| | - | DSL06-001-1LZ | OK |
| | - | DDL06-001-1LZ | NC |
| | | 06674-002-10W | NC |
| | | TSM10-012-1LW | NC |
| | | RDL06-001-10Z | OK |
| | | DSE06-001-10Z | OK |
| | | DDMX1-011-BLZ | OK |
| | | DDE06-BLZ 600W | NC |
| | SLIDE DIMMER | SURESLIDE | OK |
| | - | WHITE NO.6674 600W | OK |
| COOPER | - | AAL06-C1 | NC |
| OLEGRAND | - | RHCL453PW | OK |
| - | - | P-PKG1W-WH-R | NC |
| Wemo | - | F7C059 | NC |
| TP LINK | Kasa Smart | HS220 | NC |
| WATTSTOPPER MICO | DETECTOR | DCD267-W | OK |
| Martin Jerry | - | MJ-SD01 | OK |

**DIMMER COMPATIBILITY**

| | |
|---|---|
| OK | Dims to < 15% |
| OK | Dims to 15 - 30% |
| NC | Not Compatible |

**90+ LIGHTING NOTES**

1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
2) The results may be different for each application depending on the installation conditions.
3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.
4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.