

90+ LIGHTING



MODEL	A21 17W 1600LM 3000K GU24
SKU	SE-350.092

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DVCL-153P	OK	
		DVELV-303P-AL	OK	
		DVELC-303P-WH	OK	
		DV-600P-WH	OK	
		DVELV-300P-WH	OK	
		603P-WH	OK	
		DVSCCL-153P	NC	
		CTELV-303P	OK	
		S-600P	OK	
		CTCL-153P	NC	
	SKYLARK	SELV-300P-WH	OK	
		SLV-600-WH	OK	
		S-603P-WH	OK	
		SLV-600P	OK	
		S-600P-WH	OK	
		SCL-153P	NC	
		LGCL-153P	OK	
		LGCL-153PL	OK	
		LGCL-153PLH-WH	OK	
		-	1B3211	OK
	-	1C131I	OK	
	VIVE	MRF2S-6CL-WH	NC	
	DIVA C-L	DVWCL-153PH-WH	OK	
	MAESTRO	MAELV-600-WH	OK	
		MAELV-600	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
		NTLV-600-277-WH	OK	
		ARIADNI	AYCL-153P-WH	OK
		VIERTI	VTELV-600M	OK
		-	DVWCL-153PH/jsb1-85	OK
		-	NTLV-600-WH/jsb1-88	OK
VOVA		NTLV-600-WH	OK	
MAESTRO WIRELESS		MRF2-3LD	OK	
		MRF2S-6CL-WL	NC	
		RADIO RA2	RRD-6CL-WH	NC
	RADIO RA3	RRD-6NA	OK	
	TOGLER	TG-600PR	NC	
	GRAFIK EYE QS	QSGRJ-6P	OK	
	INOVAT	NTELV-300	OK	
	CASETA	PD-6WCL-WH	OK	
	-	MRF2-3LDH	OK	
	-	MAELV-600M	OK	
-	SCL-153P-WH	OK		
-	DVELV-300P-WH	OK		
-	6161	OK		
-	RPI06-1/jsb1-103	OK		
-	1PL06/jsb-92	OK		
-	RTD01-10Z/jsb-100	OK		
-	IPI06	OK		
-	1PL06	OK		
-	RTD01-10Z	OK		
-	6674	OK		
-	6633-P	OK		
-	52136	OK		
DECORA	R62-6674-POW	OK		
-	V47-C06579	OK		
-	L20-6602	OK		
-	DMB01/6	OK		
MAXXIMA	-	DMA02	OK	
FEIT	-	LGCL-153PLH-WH	OK	
	-	LUTRO-S-600P-WH	OK	
	-	LEVITON-C20-06681-12A	OK	

DIMMER COMPATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 - 2) The results may be different for each application depending on the installation conditions.
 - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.