

90+ LIGHTING



| | |
|-------|---------------------------------|
| MODEL | A19 9W 800LM 3000K E26 ENCLOSED |
| SKU | SE-350.070 |

| DIMMER COMPATIBILITY LIST | | | |
|---------------------------|---------------|-----------------------|---------------|
| MANUFACTURER | BRAND | DIMMER MODEL | COMPATIBILITY |
| LUTRON | DIVA | DVCL-153P | OK |
| | | DVELV-300P | OK |
| | | DVELV-303P-AL | OK |
| | | DVELC-303P-WH | OK |
| | | DV-600P-WH | OK |
| | MAESTRO | 603P-WH | OK |
| | | MAELV-600-WH | OK |
| | | CTELV-303P | OK |
| | | S-600P | OK |
| | | CTCL-153P | OK |
| | | SELV-300P-WH | OK |
| | | SLV-600-WH | OK |
| | | S-603P-WH | OK |
| | | SLV-600P | OK |
| | | S-600P-WH | OK |
| | RADIO RA2 | RRD-6NA | OK |
| | | RRD-6CL-WH | NC |
| | LUMEA | LGCL-153P | OK |
| | | LGCL-153PL | OK |
| | | LGCL-153PLH-WH | OK |
| | VIVE | MRF2S-6CL-WH | NC |
| | CASETA | PD-6WCL-WH | OK |
| | DIVA C-L | DVWCL-153PH-WH | OK |
| | SPACER | SPSELV-600M | OK |
| | NOVA T | NTELV-300-WH | OK |
| | | NTLV-600-277-WH | OK |
| | ARIADNI | AYCL-153P-WH | OK |
| | - | 1B3211 | OK |
| | - | 1C1311 | OK |
| | VIERTI | VTELV-600M | OK |
| | - | DVWCL-153PH/jsb1-85 | OK |
| | - | NTLV-600-WH/jsb1-88 | OK |
| | NOVA | NTLV-600-WH | OK |
| - | MRF2-3LDH | OK | |
| - | MACL-153M-WH | OK | |
| - | SCL-153P-WH | OK | |
| - | DVELV-300P-WH | OK | |
| LEVITON | - | IPI06 | OK |
| | - | 1PL06 | OK |
| | - | RTD01-10Z | OK |
| | - | RPI06-1/jsb1-103 | OK |
| | - | 1PL06/jsb-92 | OK |
| | - | RTD01-10Z/jsb-100 | OK |
| | - | 6161 | OK |
| | - | V47-C06579 | OK |
| | DECORA | R62-6674-P0W | OK |
| | - | 6633-P | OK |
| | - | 52136 | OK |
| | - | 6674 | OK |
| FEIT | - | LGCL-153PLH-WH | OK |
| | - | LUTRO-S-600P-WH | OK |
| | - | LEVITON-C20-06681-12A | OK |
| MAXXIMA | - | DMB01/6 | OK |
| | - | DMA02 | OK |

DIMMER COMPATIBILITY

| | |
|----|------------------|
| OK | Dims to < 15% |
| OK | Dims to 15 - 30% |
| NC | Not Compatible |

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.