90+LIGHTING



MODEL	PAR30 10W 750LM 2700K E26 LN	
SKU	SE-350.013	

DIMMER COMPATIBILITY LIST					
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY		
		DVCL-153P	OK		
		DVELV-300P	OK		
		DVELV-303P-AL	OK		
	DIVA	DVELC-303P-WH	OK		
		DV-600P-WH	OK		
		603P-WH	OK		
		DVSCCL-153P	OK		
	SKYLARK	SELV-300P	OK		
		CTELV-303P	OK		
		CTCL-153P	OK		
		S-603P-WH	OK		
		SLV-600P	OK		
		S-600P-WH	OK		
		SCL-153P-WH	OK		
	LUMEA	LGCL-153P	OK		
		LGCL-153PL	OK		
		LGCL-153PLH-WH	OK		
	VIERTI	VTELV-600M	OK OK		
	NOVA	NTLV-600-WH	OK		
		MACL-153M-WH	NC NC		
LUTRON	MAESTRO	MAELV-600-WH	OK		
	MAESTRO WIRELESS	MRF2-3LD	OK OK		
	TOGGLER	TG-600PR	OK OK		
	GRAFIK EYE OS	QSGRJ-6P	OK OK		
	INOVAT	NTELV-300	OK OK		
	CASETA	PD-6WCL-WH	NC		
	CASETA	RRD-6NA	OK		
	RADIO RA2	RRD-6CL-WH	NC		
		1B3211	OK		
	-		OK OK		
	-	1C13l1	OK OK		
	-	DVWCL-153PH/jsb1-85			
	-	NTLV-600-WH/jsb1-88	OK OK		
	-	MRF2-3LDH	OK		
		DVELV-300P-WH	OK		
	VIVE	MRF2S-6CL-WH	NC		
	DIVA C*L	DVWCL-153PH-WH	OK		
	SPACER	SPSELV-600M	OK		
	NOVA T	NTELV-300-WH	OK OK		
		NTLV-600-277-WH	OK		
	ARIADNI	AYCL-153P-WH	OK		
	DECORA	R62-6674-P0W	OK		
	-	6674	OK		
	-	6161	OK		
	-	IPI06	OK		
	-	1PL06	OK		
	-	V47-C06579	OK		
LEVITON	-	RTD01-10Z	OK		
	-	L20-6602	NC		
	-	6633-P	OK		
	-	52136	OK		
	-	RPI06-1/jsb1-103	OK		
	-	1PL06/jsb-92	OK		
	-	RTD01-10Z/jsb-100	OK		
N 4 A X (X / IN 4 A	-	DMB01/6	OK		
MAXXIMA	-	Maxxima DMA02	OK		
FEIT	-	LGCL-153PLH-WH	OK		
	-	LUTRO-S-600P-WH	OK		
	-	LEVITON-C20-06681-12A	OK		
	1				

DIMMER COMPATIBILITY

DIMINIER COM ANDIEM				
OK	Dims to < 15%			
OK	Dims to 15 - 30%			
NC	Not Compatible			

90+ LIGHTING NOTES

- 30+ LighTing NOTES
 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 2) The results may be different for each application depending on the installation conditions.
 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
 For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

