+ LIGHTING



MODEL SKU PAR30 12W 850LM 2700K E26 SE-RL6.CE11.1412G

	DIMMER CC	OMPATIBILITY LIST	
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
		DV-603P	OK
		DVWCL-153PH-WH DVW-600PH-WH	OK NC
		DV-603PH-WH	OK
		DV-600PH-WH	NC NC
	DIVA	DVCL-153PH	NC
		DVCL-153P-WH	OK
		DVWCL-153PH-WHC	OK NG
		DV-600P-WH DVCL-253PH	NC NC
		DVELV-300P-WH	OK
i T		CTCL-153P-WH	OK
		S-600PR-WH	NC
	SKYLARK	S-603PGH-WH	NC
		S-600H-WH	OK
		S-10PH SCL-153P-WH	NC NC
		S-600-IV	NC NC
		S-603PH-WH	OK
		S-600P-WH	NC
		SCL-153PH-WH	OK
		S-603P-WH	OK OK
		SELV-300P-WH SLV-600-WH	OK OK
LUTRON		D-600PH-DK	NC NC
EGINGIV		MAW-600	NC NC
		MAW-600H-AL	NC
		MACL-153M-WH	NC
	MAESTRO	MACL-153MR-WH	NC NC
		MACL-153MH-WH MSCL-OP153MH-WH	NC NC
		MACL-153MLH-WH	NC NC
		TG-603PGH-WH	NC NC
		MAELV-600-WH	OK
[=	DV-603PR	NC
l -	-	D-600RH-DK	OK
	TOGGLER	TG-600PH-WH TGCL-153PH-WH	NC OK
ļ		D-600R-WH	OK OK
	=	D-600R-IV	OK OK
İ		AYCL-153P-WH	OK
	ARIADNI	AY-600PH-WH	NC
l -		AYCL-153PH	OK
l -	VIVE	MRF2S-6CL-WH PD-6WCL-WH	OK OK
	CASETA SPACER	SPSELV-600M	OK OK
†		NTELV-300-WH	OK
	NOVA T	NTLV-600-277-WH	OK
	RADIO RA2	RRD-6CL-WH	OK
	DECORA	R62-6674-P0W	OK
	_	6684 NO.6683	NC NC
,	-	6631-LA	OK
LEVITON	-	IPI06	NC NC
	-	NO.6672	NC
	-	603-6631-A	OK
		6631-A	OK NO
	-	NO.IPL06 IPI10-1LZ	NC NC
,	<u> </u>	6683-10Z	NC NC
	-	IPI06-1LZ	NC NC
	=	NO.6631	OK
	-	6681	NC
GE	=	18024	NC NC
ALMOND CTI	-	LUXDM600-12 DM600-12-2	NC NC
CTL	<u>-</u>	DM600-12-3 SDM3/1000	OK OK
AH	_	SDM/600	OK OK
LEGRAND	-	HCL453PTC	NC NC
	-	DAL06P-C2-K	NC
COOPER	-	TAL06P-C2-K	NC
3331 EK	-	SAL06P-W-K	NC NC
MAXXIMA	-	AAL06-C1 MEW-DM600	NC OK

DIMMER COMPATIBILITY

	DIIVIIVIER COIVII ATIDIETTI
1	OK
Ì	OK
Ì	NC

Dims to < 15% Dims to 15 - 30% Not Compatible

- 90+ LIGHTING NOTES

 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.

 2) The results may be different for each application depending on the installation conditions.

 3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.

 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.

 For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

