

# 90+ LIGHTING



MODEL	A19 10W 800LM 3000K E26 PF.7
SKU	SE-350.050

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DVCL-153P	OK	
		DVELV-300P	OK	
		DVELV-303P-AL	OK	
		DVELC-303P-WH	OK	
		DV-600P-WH	OK	
		DVELV-300P-WH	OK	
		603P-WH	OK	
	DVSCCL-153P	OK		
	SKYLARK	SELV-300P	OK	
		CTELV-303P	OK	
		S-600P	OK	
		CTCL-153P	OK	
		SELV-300P-WH	OK	
		SLV-600-WH	NC	
		S-603P-WH	OK	
		SLV-600P	OK	
		S-600P-WH	OK	
		LUMEA	LGCL-153PL	OK
	LGCL-153PLH-WH		OK	
	LGCL-153P		OK	
	-	1B3211	OK	
	-	1C1311	OK	
	VIVE	MRF2S-6CL-WH	NC	
	CASETA	PD-6WCL-WH	NC	
	DIVA C*L	DVWCL-153PH-WH	NC	
	MAESTRO	MAELV-600-WH	OK	
		MAELV-600	OK	
		MAELV-153M	OK	
		SPACER	SPSELV-600M	OK
		NOVA T	NTELV-300-WH	OK
		ARIADNI	NTLV-600-277-WH	NC
		VIERTI	AYCL-153P-WH	OK
		-	VTCLV-600M	OK
		-	DVWCL-153PH/jsb1-85	OK
		-	NTLV-600-WH/jsb1-88	OK
	NOVA	NTLV-600-WH	OK	
	MAESTRO WIRELESS	MRF2-3LD	OK	
	RADIO RA2	RRD-6CL	OK	
	RADIO RA3	RRD-6CL-WH	NC	
	TOGGLER	RRD-6NA	OK	
GRAFIK EYE QS	TG-600PR	OK		
INOVA	QSGRJ-6P	OK		
CASSETA	NTELV-300	OK		
-	PD-6WCL	OK		
-	MRF2-3LDH	OK		
-	MAELV-153M-WH	OK		
-	SCL-153P-WH	OK		
-	DVELV-300P-WH	OK		
LEVITON	-	RPI06-1/jsb1-103	OK	
	-	1PL06/jsb-92	OK	
	-	RTD01-10Z/jsb-100	OK	
	-	IPI06	OK	
	-	1PL06	OK	
	-	RTD01-10Z	OK	
	-	6674	OK	
	-	6633-P	OK	
	-	52136	OK	
	DECORA	R62-6674-POW	OK	
	-	V47-C06579	OK	
	-	6161	OK	
	-	L20-6602	OK	
	FEIT	-	LGCL-153PLH-WH	OK
		-	LUTRO-S-600P-WH	OK
-		LEVITON-C20-06681-12A	OK	
MAXXIMA	-	DMB01/6	OK	
	-	DMA02	OK	

### DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

### 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps. For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.