

# 90+ LIGHTING



MODEL	MR16 7W 420LM 2700K GU5.3 10D
SKU	SE-350.001

DIMMER COMPATIBILITY LIST								
MANUFACTURER	BRAND	DIMMER MODEL	TRANSFORMER	COMPATIBILITY				
				LIGHTTECH LET-60	HATCH RS12-60M	HATCH RS12-60M-LED	LIGHTTECHINC LET 75	Trancil - THLED 50W (MAGNETIC)
LUTRON	VIVE	MRF2S-6CL-WH		OK	NC	NC	-	-
	CASETA	PD-6WCL-WH		OK	NC	NC	-	-
	DIVA	DVELV-300P-WH		OK	OK	OK	OK	OK
		DVSCCL-153P		OK	OK	NC	-	OK
	MAESTRO	MACL-153M-WH		OK	OK	NC	-	OK
		MRF2-3LD		OK	OK	OK	OK	OK
	SKYLARK	SCL-153P-WH		OK	OK	NC	OK	OK
		CTCL-153P		OK	OK	NC	-	OK
		SLV-600P		-	OK	NC	-	-
	RADIO RA2	RRD-6CL-WH		OK	NC	NC	-	OK
		RRD-H6BRL		-	NC	NC	-	-
		RD-RD		-	NC	NC	-	-
	TOGGLER	TG-600PR		OK	OK	NC	-	NC
	GRAKIF EYE	-		-	OK	NC	-	-
	INOVAT	NTELV-300		-	OK	OK	-	-
GRAPHIKG EYE QS	QSGRJ-6P		OK	OK	NC	-	OK	
LEVITON	-	6602-IW		OK	OK	OK	-	NC
	-	L20-6602		-	NC	NC	-	-
LEGRAND	PASS & SEYMOUR	DDH16PWV		NC	NC	NC	-	NC
COOPER	COOPER	Aspire		NC	NC	NC	-	NC
LUTRON	CREDENZA	TTCL-100		NC	NC	NC	-	NC

**DIMMER COMPATIBILITY**

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

## 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.  
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.