

90+ LIGHTING



MODEL	MR16 7W 480LM 2700K GU5.3 24D
SKU	SE-350.002

DIMMER COMPATIBILITY LIST								
MANUFACTURER	BRAND	DIMMER MODEL	TRANSFORMER	COMPATIBILITY				
				LIGHTECH LET-60	HATCH RS12-60M	HATCH RS12-60M-LED	LIGHTECHINC LET 75	Trancil - THLED 50W (MAGNETIC)
LUTRON	VIVE	MRF2S-6CL-WH		-	NC	NC	-	-
	CASETA	PD-6WCL-WH		-	NC	NC	-	-
	DIVA	DVELV-300P-WH		OK	OK	OK	OK	OK
		DVSCCL-153P		OK	OK	NC	-	OK
	MAESTRO	MACL-153M-WH		OK	OK	NC	-	NC
		SCL-153P-WH		OK	OK	NC	OK	OK
	SKYLARK	CTCL-153P		OK	OK	NC	-	OK
		SLV-600P		-	OK	NC	-	-
		RRD-6CL-WH		OK	NC	NC	-	OK
	RADIO RA2	RD-RD		-	NC	NC	-	-
		RRD-H6BRL		-	NC	NC	-	-
	-	MRF2-3LD		OK	OK	NC	OK	OK
	TOGGLER	TG-600PR		OK	OK	NC	-	NC
	GRAPHIK EYE OS	QSGRJ-6P		OK	OK	OK	-	OK
	GRAKIF EYE	-		-	OK	OK	-	-
INOVAT	NTELV-300		-	OK	OK	-	-	
LEVITON	-	6602-IW	OK	OK	NC	-	NC	
-	-	L20-6602	-	NC	NC	-	-	
LEGRAND	PASS & SEYMOUR	DDH16PWV	NC	NC	NC	-	NC	
COOPER	COOPER	ASPIRE	NC	NC	NC	-	NC	
LUTRON	CREDENZA	TTCL-100	NC	NC	NC	-	NC	

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.