## 90+LIGHTING



MODEL	G16.5 5W 350LM 3000K E12 Clear	
SKU	SE-350.034	

DIMMER COMPATIBILITY LIST					
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY		
	VIVE	MRF2S-6CL-WH	NC		
	CASETA	PD-6WCL-WH	NC		
	MAESTRO	MAELV-600	OK		
	MALSTRO	MACL-153M-WH	NC		
		SELV-300P	NC		
	SKYLARK	CTELV-303P	OK		
		CTCL-153P	OK		
		S-603P-WH	NC		
		SLV-600P	NC		
		SCL-153P-WH	NC		
		S-600P-WH	OK		
		DVELV-300P-WH	OK		
	DIVA	DVELV-303P-AL	OK		
		DVELC-303P-WH	OK		
	5.,,,	DV-600P-WH	NC		
		603P-WH	OK		
		DVCL-153P	OK		
LUTRON	DIVA C*L	DVWCL-153PH-WH	OK		
		LGCL-153P	OK		
	LUMEA	LGCL-153PL	OK		
		LGCL-153PLH-WH	OK		
	VIERTI	VTELV-600M	OK		
	NOVA	NTLV-600-WH	OK		
	SPACER	SPSELV-600M	OK		
		NTELV-300-WH	NC		
	NOVA T	NTLV-600-277-WH	OK		
		NTLV-600-WH/jsb1-88	OK		
	RADIO RA2	RRD-6CL-WH	NC		
	ADIADAII	RRD-6NA	OK		
	ARIADNI	AYCL-153P-WH	OK		
	=	183211	OK		
	=	1C13l1	OK OK		
	=	VTELV-600M	OK OK		
_	=	SLV-600P	OK OK		
	=	MRF2-3LDH			
LEVITON	<u>-</u>	6674 6161	OK OK		
	<del>_</del>	IPI06	OK OK		
	<del>_</del>	1PL06	OK OK		
	<del>_</del>	V47-C06579	OK OK		
	<del>_</del>	RTD01-10Z	OK OK		
	DECORA	R62-6674-P0W	OK OK		
	- DECORA	6674	OK OK		
		6633-P	OK OK		
	<del>_</del>	52136	OK OK		
	<del>-</del>	6161	OK OK		
		RPI06-1/jsb1-103	OK		
	<u>-</u>	1PL06/jsb-92	OK OK		
	<del>-</del>	RTD01-10Z/jsb-100	OK OK		
		DMB01/6	OK OK		
MAXXIMA	=	DMA02	OK		
		LGCL-153PLH-WH	OK OK		
FEIT		LUTRO-S-600P-WH	OK		
		LEVITON-C20-06681-12A	OK OK		
		LLV11014 020 00001 12/1	- OA		

## DIMMED COMPATIBILITY

DIMINIER CONFATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

## 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
  2) The results may be different for each application depending on the installation conditions.
  3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.
  4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
  For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

