90+LIGHTING



MODEL	G25 7W 500LM 2700K E26 Clear
SKU	SE-350.037

		OMPATIBILITY LIST	
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
		DVCL-153P	OK
		DVELV-300P-WH	OK
		DVELV-303P-AL	OK
	DIVA	DVELC-303P-WH	OK
		DV-600P-WH	OK
		DVELV-300P	OK
		603P-WH	OK
		DVWCL-153PH	OK
		DVSCCL-153P	OK
	SKYLARK	S-603P-WH	OK
		SLV-600P	OK
		S-600P-WH	OK
		SCL-153P-WH	OK
		SELV-300P	OK
		CTELV-303P	OK
		S-600P	OK
		CTCL-153P	OK
		SELV-300P-WH	OK
		SLV-600-WH	OK
Ī	DIVA C*L	DVWCL-153PH-WH	OK
Ī		LGCL-153P	OK
	LUMEA	LGCL-153PL	OK
		LGCL-153PLH-WH	OK
	VIERTI	VTELV-600M	OK
LUTRON	NOVA	NTLV-600-WH	OK
		MACL-153M	OK
		MAELV-600	OK
	MAESTRO	MACL-153M-WH	OK
		MAELV-600-WH	OK
The state of the s	MAESTRO WIRELESS	MRF2-3LD	OK
<u> </u>	IVI/ LESTING VVIINELESS	RRD-6CL	OK
	RADIO RA2	RRD-6NA	OK
		RRD-6CL-WH	OK
	TOGGLER	TG-600PR	OK
H	GRAFIK EYE OS	OSGRJ-6P	OK
	INOVAT	NTELV-300	OK
	-	1B3211	OK
	_	1C13I1	OK
-	-	VTELV-600M	OK
-	-	SLV-600P	OK
-	-	MRF2-3LDH	OK OK
-	- VIVE	MRF2-3LDH MRF2S-6CL-WH	OK
-	CASETA	PD-6WCL-WH	
-			OK
ļ-	CASSETA SPACER	PD-6WCL	OK OK
<u> </u>	SPACER	SPSELV-600M	OK OK
	NOVA T	NTELV-300-WH	OK OK
		NTLV-600-277-WH	OK
Ļ		NTLV-600-WH/jsb1-88	OK
	ARIADNI	AYCL-153P-WH	OK OK
Ļ	DECORA	R62-6674-P0W	OK OK
Ļ	-	6674	OK
ļ	-	6633-P	OK
<u> </u>	-	52136	OK
L	-	6161	OK
<u> </u>	-	IPI06	OK
LEVITON	-	1PL06	OK
		V47-C06579	OK
	-	RTD01-10Z	OK
	-	L20-6602	OK
Ţ	-	RPI06-1/jsb1-103	OK
Ţ	-	1PL06/jsb-92	OK
Ţ	-	RTD01-10Z/jsb-100	OK
N	-	DMB01/6	OK
MAXXIMA	-	DMA02	OK
	-	LGCL-153PLH-WH	OK
FEIT	-	LUTRO-S-600P-WH	OK
FEII			

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

