

90+ LIGHTING



MODEL	A19 10W 800LM 3000K E26 PF.7
SKU	SE-350.050

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DVCL-153P	OK	
		DVELV-300P	OK	
		DVELV-303P-AL	OK	
		DVELC-303P-WH	OK	
		DV-600P-WH	OK	
		DVELV-300P-WH	OK	
		603P-WH	OK	
		DVWCL-153PH	OK	
		DVSCCL-153P	OK	
		SELV-300P	OK	
	SKYLARK	CTELV-303P	OK	
		S-600P	OK	
		CTCL-153P	OK	
		SELV-300P-WH	OK	
		SLV-600-WH	NC	
		S-603P-WH	OK	
		SLV-600P	OK	
		S-600P-WH	OK	
		LGCL-153PL	OK	
		LGCL-153PLH-WH	OK	
	LUMEA	LGCL-153P	OK	
		-	1B3211	OK
		-	1C1311	OK
		VIVE	MRF2S-6CL-WH	NC
		CASETA	PD-6WCL-WH	NC
		DIVA C*L	DVWCL-153PH-WH	NC
		MAESTRO	MAELV-600-WH	OK
			MAELV-600	OK
			MAELV-153M	OK
		SPACER	SPSELV-600M	OK
	NOVA T	NTELV-300-WH	OK	
		NTELV-600-277-WH	NC	
	ARIADNI	AYCL-153P-WH	OK	
	VIERTI	VTELV-600M	OK	
	-	DVWCL-153PH/jsb1-85	OK	
	-	NTELV-600-WH/jsb1-88	OK	
	NOVA	NTELV-600-WH	OK	
	MAESTRO WIRELESS	MRF2-3LD	OK	
	RADIO RA2	RRD-6CL	OK	
		RRD-6CL-WH	NC	
	RADIO RA3	RRD-6NA	OK	
	TOGLER	TG-600PR	OK	
GRAFIK EYE QS	QSGRJ-6P	OK		
INOVAT	NTELV-300	OK		
CASETA	PD-6WCL	OK		
-	MRF2-3LDH	OK		
-	MAELV-153M-WH	OK		
-	SCL-153P-WH	OK		
-	DVELV-300P-WH	OK		
-	RPI06-1/jsb1-103	OK		
-	1PL06/jsb-92	OK		
-	RTD01-10Z/jsb-100	OK		
-	IPI06	OK		
-	1PL06	OK		
-	RTD01-10Z	OK		
-	6674	OK		
-	6633-P	OK		
-	52136	OK		
DECORA	R62-6674-POW	OK		
-	V47-C06579	OK		
-	6161	OK		
-	L20-6602	OK		
FEIT	LGCL-153PLH-WH	OK		
	LUTRO-S-600P-WH	OK		
	LEVITON-C20-06681-12A	OK		
MAXXIMA	DMB01/6	OK		
	DMA02	OK		

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps. For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.