H LIGHTIN



MODEL SKU

RETROFIT DOWNLIGHT 15W 5" to 6" 1100LM 4000K E26

SE-350.065

DIMMER COMPATIBILITY LIST			
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
		DVCL-153P	OK
		DVELV-303P-AL	OK
		DVELC-303P-WH	ОК
	DIVA	DV-600P-WH	OK
		DVELV-300P-WH	OK
		603P-WH	OK
		DVSCCL-153P	OK
	DIVA C*L	DVWCL-153PH-WH	OK
		MAELV-600-WH	OK
	MAESTRO	MACL-153M	OK
	MAESTRO WIRELESS	MRF2-3LD	OK
		CTELV-303P	OK
		CTCL-153P	OK OK
		SELV-300P-WH	NC
	SKYLARK	SLV-500F-WIT	OK
		S-603P-WH	OK
		SLV-600P	OK
		S-600P-WH	OK
	LUMEA	LGCL-153P	OK
		LGCL-153PL	OK
		LGCL-153PLH-WH	OK
LUTRON	-	1B3211	OK
	-	1C13l1	OK
	VIVE	MRF2S-6CL-WH	ОК
	CASETA	PD-6WCL-WH	OK
	SPACER	SPSELV-600M	OK
	NOVA T	NTELV-300-WH	OK
	NOVAT	NTLV-600-277-WH	ОК
	RADIO RA2	RRD-6CL-WH	OK
	RADIO RA3	RRD-6NA	OK
	ARIADNI	AYCL-153P-WH	OK
	VIERTI	VTELV-600M	ОК
	-	DVWCL-153PH/jsb1-85	OK
	-	NTLV-600-WH/jsb1-88	OK
	NOVA	NTLV-600-WH	OK
	TOGGLER	TG-600PR	OK
	GRAFIK EYE QS	QSGRJ-6P	ОК
	INOVAT	NTELV-300	OK
	CASSETA	PD-6WCL	OK
	-	MRF2-3LDH	OK OK
		MACL-153M-WH	OK
		SCL-153P-WH	OK
		DVELV-300P-WH	OK
	-	6674	OK
LEVITON	-	6633-P	OK
	-	52136	OK
	 DECORA	R62-6674-POW	OK
	DECORA	V47-C06579	OK OK
	-	6161 DDIOG 1/iab1 102	OK
	-	RPI06-1/jsb1-103	OK
	-	1PL06/jsb-92	OK
	-	RTD01-10Z/jsb-100	OK
	-	IP106	OK
	-	1PL06	OK
	-	RTD01-10Z	OK
	-	L20-6602	OK
MAXXIMA	-	DMB01/6	OK
	-	DMA02	ОК
	-	LGCL-153PLH-WH	ОК
FEIT	-	LUTRO-S-600P-WH	ОК
	-	LEVITON-C20-06681-12A	ОК
	+ +		•

DIMMER COMPATIBILITY

BINNEROONNACTIBLETT	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
2) The results may be different for each application depending on the installation conditions.
3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.

4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps. For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

