H LIGHTING MODEL SKU A19 10W 800LM 2700K GU24

SE-350.089



DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
	DIVA	DVCL-153P	OK	
		DVELV-303P-AL	OK	
		DVELC-303P-WH	OK	
		DV-600P-WH	OK OK	
		DVELV-300P-WH 603P-WH	OK	
		DVSCCL-153P	OK	
		MAELV-600-WH	OK OK	
	MAESTRO WIRELESS	MACL-153M	OK OK	
	SKYLARK	CTELV-303P	OK	
		CTCL-153P	OK	
		SELV-300P-WH	ОК	
		SLV-600-WH	ОК	
		S-603P-WH	OK	
		SLV-600P	OK	
		S-600P-WH	OK	
	LUMEA	LGCL-153P	OK	
		LGCL-153PL	OK	
LUTRON		LGCL-153PLH-WH	OK	
	-	1B3211	OK	
	-	1C13I1	OK	
	VIVE	MRF2S-6CL-WH	OK	
	CASETA	PD-6WCL-WH	OK	
		PD-6WCL	OK	
	DIVA C*L	DVWCL-153PH-WH	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
		NTLV-600-277-WH	OK	
	INOVAT	NTELV-300	ОК	
	ARIADNI	AYCL-153P-WH	OK	
	VIERTI	VTELV-600M	OK	
	-	DVWCL-153PH/jsb1-85	OK	
	-	NTLV-600-WH/jsb1-88	OK	
		NTLV-600-WH	OK	
	MAESTRO WIRELESS	MRF2-3LD	OK	
	RADIO RA2	RRD-6CL	OK	
	RADIO RA3	RRD-6CL-WH RRD-6NA	OK OK	
	TOGGLER	TG-600PR	OK OK	
	GRAFIK EYE QS	QSGRJ-6P	OK OK	
	GRAFIK EYE QS	MRF2-3LDH	OK OK	
		MACL-153M-WH	OK OK	
		SCL-153P-WH	OK OK	
		DVELV-300P-WH	OK	
		6674	OK	
LEVITON		6633-P	OK	
		52136	OK	
	DECORA	R62-6674-P0W	OK	
	-	V47-C06579	OK	
		6161	OK	
	-	RPI06-1/jsb1-103	OK	
	-	1PL06/jsb-92	OK	
	-	RTD01-10Z/jsb-100	OK	
	-	IPI06	OK	
	-	1PL06	OK	
	-	RTD01-10Z	OK	
	-	L20-6602	OK	
	-	LGCL-153PLH-WH	OK	
FEIT	-	LUTRO -S-600P-WH	OK	
	-	LEVITON-C20-06681-12A	OK	
MAXXIMA	-	DMB01/6	ОК	
IVIAAAIIVIA	-	DMA02	OK	

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
2) The results may be different for each application depending on the installation conditions.
3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.

4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps. For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

