

90+ LIGHTING



MODEL	ST21 3.8W 350LM 2200K E26
SKU	SE-350.124

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	LOAD	COMPATIBILITY
LUTRON	VIVE	MRF2S-6CL-WH		OK
	CASETA	PD-6WCL-WH		NC
	DIVA	DV-600P-WH		NC
		DVELV-300P-WH		OK
	DIVA C*L	DVWCL-153PH-WH		OK
	MAESTRO	MAELV-600-WH		NC
		MAELV-600-WH		OK
	SKYLARK	S-603P-WH		NC
		SCL-153P-WH		NC
		SELV-300P-WH		OK
		SLV-600-WH		NC
	SPACER	SPSELV-600M		OK
	NOVA T	NTELV-300-WH		OK
		NTELV-300-WH		OK
RADIO RA2	RRD-6CL-WH		OK	
-	CT-600PR-WH		OK	
LEVITON	ARIADNI	AYCL-153P-WH		NC
	DECORA	R62-6674-P0W		NC
	-	R70-6631-1LW		OK
	-	C22-6672-1LW		OK

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.