H LIGHTING



MODEL SKU

CA11 4W 400LM 2700K E12 SE-350.195

DIMMER COMPATIBILITY LIST			
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
	DIVA	DV-600P-WH	NC
		DVELV-300P-WH	OK
	-	MACL-153MR-WH	OK
	-	CT-600PR-WH	ОК
	-	TG600P	ОК
	-	Т90В6	OK
	-	S600	OK
	MAESTRO	MRF2S-6CL-WH	NC
LUTRON		MACL-153M-WH	OK
		MAELV-600-WH	ОК
	Caseta	PD-6WCL-WH	NC
	DIVA C*L	DVWCL-153PH-WH	NC
	Skylark	S-603P-WH	NC
		SCL-153P-WH	NC
-		SELV-300P-WH	OK
		SLV-600-WH	NC
	Spacer	SPSELV-600M	ОК
	NOVA T	NTELV-300-WH	ОК
		NTLV-600-277-WH	ОК
	Radio RA2	RRD-6CL-WH	NC
	Ariadni	AYCL-153P-WH	NC
LEVITON	Decora	R62-6674-P0W	NC

DIMMER COMPATIBILITY

OK	Dims to < 15%	
ОК	Dims to 15 - 30%	
NC	Not Compatible	

90+ LIGHTING NOTES

90+ LIGHTING NOTES
1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
2) The results may be different for each application depending on the installation conditions.
3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.
4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

