

90+ LIGHTING



MODEL	MR16 5W 25° 365lm 2700K GU5.3 12V COB DIMMABLE
SKU	SE-350.164

DIMMER COMPATIBILITY LIST								
MANUFACTURER	BRAND	DIMMER MODEL	TRANSFORMER	COMPATIBILITY				
				LIGHTTECH LET-60	HATCH RS12-60M	C-60	C-150	WACLIGHTING EN-1275-R-AR
LUTRON	VIVE	MRF2S-6CL-WH		NC	NC	-	-	-
	CASETA	PD-6WCL-WH		OK	OK	-	-	-
	DIVA	DV-600P-WH		OK	OK	-	-	-
		DVELV-300P-WH		NC	NC	NC	NC	OK
	DIVA C*L	DVLV-600P-WH		-	-	OK	OK	OK
		DVWCL-153PH-WH		NC	NC	-	-	-
	MAESTRO	MACL-153M-WH		OK	NC	-	-	-
		MAELV-600-WH		OK	NC	-	-	-
	SKYLARK	S-603P-WH		OK	OK	-	-	-
		SELV-300P-WH		NC	NC	-	-	-
		SCL-153P-WH		NC	NC	-	-	-
		SLV-600-WH		OK	NC	-	-	-
	SPACER	SPSELV-600M		NC	NC	-	-	-
	NOVA T	NTELV-300-WH		NC	NC	-	-	-
		NTLV-600-277-WH		OK	OK	-	-	-
	NOVA	NTLV-600-WH		-	-	OK	NC	OK
	RADIO RA2	RRD-6CL-WH		NC	NC	-	-	-
	ARIADNI	AYCL-153P-WH		NC	NC	-	-	-
TOGGLER	AYLV-600P-WH		-	-	OK	OK	OK	
-	MRF2-3LD		-	-	OK	OK	OK	
LEVITON	DECORA	R62-6674-P0W		OK	NC	-	-	-
LEGRAND	PASS & SEYMOUR	DLV703P		-	-	OK	OK	OK

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 - 2) The results may be different for each application depending on the installation conditions.
 - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.