H LIGHTING 9



CANDLE 4.5W 350LM 2700K E12 SE-RL6.CP05.1105



	DIMME	R COMPATIBILITY LIST	
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
		DV-603P	OK
LUTRON		DV-603PR	OK
	DIVA	DV-600P-WH	NC
		DVELV-300P-WH	OK
		DVW-600PH-WH	OK
	Binn	DV-600PH-WH	OK
		D-600RH-DK	OK
		DVCL-153PH	OK
		DV-603PH-WH	OK
		DVCL-153P-WH	NC
	-	S-600	OK
	LUMEA	LGCL-153CL	NC
	SKYLARK	CT-103P-WH CTCL-153P-WH	OK
		S-600PR-WH	NC OK
		S-603P-WH	NC
		SELV-300P-WH	OK
		SLV-500F-WIT	OK
		S-603PGH-WH	NC
		S-600H-WH	OK
		S-10PH	NC
		SCL-153P-WH	OK
		S-600-IV	OK
		S-600-AL	OK
		S-603PH-WH	OK
		TGCL-153PH-WH	NC
	TOGGLER	TGCL-153PLH-WH	OK
		TG-600PH-WH	OK
		TG-600PH-IV	OK
	-	D-600PH-DK	ОК
	-	MAW-600	NC
	-	D-600PH-3CK	NC
	MAESTRO	MAW-600H-WH	NC
		MACL-153M-WH	OK
		MAELV-600-WH	OK
		MAW-600H-AL	NC
	-	DVWCL-153PH-WH	OK
	VIVE	MRF2S-6CL-WH	OK
	CASETA	PD-6WCL-WH	OK
	SPACER	SPSELV-600M	OK
	NOVA T	NTELV-300-WH	OK
		NTLV-600-277-WH	OK
	RADIO RA2	RRD-6CL-WH	NC
	ARIADNI	AYCL-153P-WH	OK
	-	D-600R-IV	NC
	-	D-600R-WH	NC
	-	6683-IW	NC
Ļ	-	6631-LA	OK
Ļ	-	IPI06	NC
	-	S-600P-WH	NC
	-	6684	OK
4	-	6683 NO 6672	NC
LEVITON	-	NO.6672	OK
	-	603-6631-A 6631-A	OK OK
H	-	NO.IPL06	OK OK
-	-	6683-10Z	OK
	- DECORA	R62-6674-POW	NC
		IPI06-1LZ	OK
	-	NO.6631	NC
	-	HCL453PTC	OK
TOP	-	HCL453PTC HCL453PW	OK OK
АН	-	SDM/600	NC
GE	-	18024	NC
ALMOND		LUXDM600-12	OK
ALIVIONU	-		UN

DIMMER COMPATIBILITY

ns to < 15%
1010 - 10/0
ns to 15 - 30%
t Compatible
1

90+ LIGHTING NOTES

1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.

This diminist comparison comparison of the provided by 90° Eighting as a guidance for selecting a diminer and ramp combine 2) The results may be different for each application depending on the installation conditions.
90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps. For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

