

90+ LIGHTING



MODEL	G16.5 5W 350LM 3000K E26 Clear
SKU	SE-350.036

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	VIVE	MRF2S-6CL-WH	NC	
	CASETA	PD-6WCL-WH	NC	
	MAESTRO	MAELV-600		OK
		MAELV-600		OK
	SKYLARK	MAELV-600		OK
		MAELV-600		OK
	DIVA	MAELV-600		OK
		MAELV-600		OK
	DIVA C+L	DVWCL-153PH-WH		OK
	LUMEA	LGCL-153P		OK
		LGCL-153PL		OK
	VIERTI	VTCLV-600M		OK
	NOVA	NTLV-600-WH		OK
	SPACER	SPSELV-600M		NC
	NOVA T	NTLV-300-WH		NC
		NTLV-600-277-WH		OK
NTLV-600-WH/jsb1-88			OK	
RADIO RA2	RRD-6CL-WH		NC	
	RRD-6NA		OK	
ARIADNI	AYCL-153P-WH		OK	
-	1B3211		OK	
-	1C1311		OK	
-	VTCLV-600M		OK	
-	SLV-600P		OK	
-	MRF2-3LDH		OK	
LEVITON	-	6674	OK	
	-	6161	OK	
	-	IP106	OK	
	-	1PL06	OK	
	-	V47-C06579	OK	
	-	RTD01-10Z	OK	
	DECORA	R62-6674-P0W		OK
	-	6674		OK
	-	6633-P		OK
	-	52136		OK
	-	6161		OK
	-	RPI06-1/jsb1-103		OK
	-	1PL06/jsb-92		OK
	-	RTD01-10Z/jsb-100		OK
	MAXXIMA	-	DMB01/6	OK
-		DMA02	OK	
FEIT	-	LGCL-153PLH-WH	OK	
	-	LUTRO-S-600P-WH	OK	
	-	LEVITON-C20-06681-12A	OK	

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.