



G24q PL-V Compatible Ballast List

NC	Incompatible	P	PF <0.85
N	Acoustic noise >20dB	T	THD >30%
S	Can't start-up	C	Compatible
F	Flicker after >2s st /		Not tested
HT	High temperature	NA	Not applicable

P, T	347, NC	480, NC
	347, F	480, F
	347, P	480, P
	347, T	480, T
	347, P, T	480, P, T
	347, C	480, C
	347, S	480, S

No	Ballast No.	Ballast Description						DR PL-9W			
		Ballast Brand	Part Number	Start Method	# of Lamps	Target Replacement Lamp Type	Lamp Connection	N-1 Lamp		N Lamp	
								120	277	120	277
1	PL-76	Fulham	WH2-120-C	IS	2	13W*2 ; 13W*1 ; 18W*2 ; 18W*1 ; 26W*1	Parallel	T	NA	T	NA
2	PL-77	Fulham	WH2-120-L	IS	2	13W*2 ; 13W*1 ; 18W*2 ; 18W*1 ; 26W*1	Parallel	T	NA	T	NA
3	PL-28	ProLume	EP2CF18PS/MV/DC/K	PS	2	18W*2 ; 18W*1 ; 26W*1	Series	C	C	C	C
4	PL-52	KEYSTONE	KTEB-218-UV-RS-DW	RS	2	18W*2 ; 18W*1 ; 26W*1	Series	C	C	C	C
5	PL-53	KEYSTONE	KTEB-218-UV-PS-DW	PS	2	18W*2 ; 18W*1 ; 26W*1	Series	C	C	C	C
6	PL-63	HATCH	HC218PS/UV/D	PS	2	18W*2 ; 18W*1 ; 26W*1	Series	C	C	C	C
7	PL-13	ESPEEN	VE126120MR	PS	1	26W*1	n. a	NA	NA	P, T	NA
8	PL-70	KEYSTONE	KTEB-126-1-TP-SC-RJS /HB	PS	1	26W*1	n. a	NA	NA	P, T	NA
9	PL-71	KEYSTONE	KTEB-126-1-TP	PS	1	26W*1	n. a	NA	NA	P, T	NA
10	PL-69	KEYSTONE	KTEB-226-1-TP	PS	2	26W*2	Series	NA	NA	F	NA
11	PL-94	TOSPO	TP120-2/26 RS UPL	RS	2	26W*2	Series	NA	NA	F	NA
12	PL-201	Fulham (PONY)	NPY-120-226CFL		2	26W*2		P, T	NA	P, T	NA
13	PL-202	MOTORALA	M2-CF-26-B-S-277	RS	2	26W*2	Series	NA	NA	C	NA
14	PL-40	Philips-Advance	ICF-2S26-H1-LD	PS	2	26W*2 ; 26W*1	Series	C	C	C	C
15	PL-34	Fulham (PONY)	NPY-120-126CFL	RS	1	26W*1 ; 32W*1	n. a	NA	NA	P, T	NA
16	PL-35	Fulham(WORKHORSE)	WH3-120-C	IS	2	18W*2 ; 26W*1 ; 32W*1	Parallel	T	NA	T	NA
17	PL-19	HOWARD INDUSTRIES	EP2/42CF/MV/2	PS	2	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1	Series	C	P	C	P
18	PL-30	ProLume	EP2CF42PS/MV/DC/K	PS	2	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1	Series	C	P	C	P
19	PL-45	AC ELECTRONICS	CSD-UV42PS	PS	2	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1	Series	C	P, T	C	C
20	PL-48	KEYSTONE	KTEB-242-UV-RS-DW	RS	2	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1	Series	NA	NA	C	C
21	PL-68	Universal Lighting Technol	C242UNVMES	PS	2	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1	Series	C	P	C	C
22	PL-46	General Electric	GEC242-MVPS-3W	PS	2	26W*2 ; 32W*2 ; 42W*2 ; 42W*1	Series	C	P, T	C	T
23	PL-75	Fulham	RHA-UNV-242-C	PS	2	26W*2 ; 32W*2 ; 42W*2 ; 42W*1	Series	C	P	C	P
24	PL-3	SUNPARK	U-226PS-W	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
25	PL-12	HATCH	HC226PS/UV/D	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	P	C	C
26	PL-22	Fulham	RHA-UNV-226-C	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
27	PL-29	ProLume	EP2CF26PS/MV/DC/K	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
28	PL-37	GE	GEC226-MVPS-3W	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	P, T	C	C
29	PL-42	Universal Lighting Technol	C2642UNVME	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
30	PL-44	AC ELECTRONICS	CSS-UV42PS	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
31	PL-47	Philips-Advance	ICF-2S26-M1-BS	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
32	PL-50	KEYSTONE	KTEB-226-UV-RS-DW	RS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
33	PL-51	KEYSTONE	KTEB-226-UV-PS-DW	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	P	C	C
34	PL-55	OSRAM SYLVANIA	QTP 2x26CF/UNV DM	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
35	PL-88	Universal Lighting Technol	C2642UNVBE	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	C	C	C
36	PL-91	Philips-Advance	RCF-2S26-M1-LS-QS	RS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	NA	C	NA
37	PL-65	HOWARD INDUSTRIES	EP2/26CF/MV/2	PS	2	26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	P	C	C
38	PL-10	OSRAM SYLVANIA	QTP 2x26/32/42CFUNV DM PEM	PS	2	26W*2 ; 32W*2 ; 42W*2	Series	F	P, T	F	F
39	PL-39	Philips-Advance	ICF-2S42-M2-LD	PS	2	26W*2 ; 32W*2 ; 42W*2	Series	C	P	C	P
40	PL-43	HATCH	HC242PS/UV/D	PS	2	26W*2 ; 32W*2 ; 42W*2	Series	C	P	C	P
41	PL-56	OSRAM SYLVANIA	QTP 2x26/32/42CFUNV DM	PS	2	26W*2 ; 32W*2 ; 42W*2	Series	F	P, T	F	F
42	PL-58	Fulham	WH3-120-L	IS	2	26W*2 ; 32W*1 ; 42W*1	Parallel	T	NA	T	NA
43	PL-60	KEYSTONE	KTEB-142T-1-TP-SC /HB	PS	1	26W*1 ; 32W*1 ; 42W*1	n. a	NA	NA	P, T	NA
44	PL-61	Robertson	RS0142TR120	RS	1	26W*1 ; 32W*1 ; 42W*1	n. a	NA	NA	P, T	NA
45	PL-87	OSRAM SYLVANIA	QTP 2x26/32/42CF/UNV TM	RS	2	26W*2 ; 32W*2 ; 42W*2	Series	F	P, T	F	F
46	PL-57	TOPAZ	B2642UNV/ME-TPZ	PS	2	18W*2 ; 26W*2 ; 26W*1 ; 32W*1 ; 42W*1	Series	C	P, T	C	C
47	PL-38	DAMAR	23350D	PS	2	13W*2 ; 13W*1 ; 18W*2 ; 18W*1	Series	C	C	C	C
48	PL-4	SUNPARK	SL27T	PS	2	13W*2 ; 18W*2	Series	NA	NA	P, T	NA

49	PL-27	ProLume	EP2CF13PS/MV/DC/K	PS	2	13W*2 ; 13W*1 ; 18W*1	Series	C	C	C	C
50	PL-62	HATCH	HC213PS/UV/D	PS	2	13W*2 ; 13W*1 ; 18W*1	Series	C	T	C	C
51	PL-64	HOWARD INDUSTRIES	EP2/13CF/MV/2	PS	2	13W*2 ; 13W*1 ; 18W*1	Series	C	C	C	C
52	PL-14	ESPEN	VE118120MR	PS	1	18W*1	n. a	NA	NA	P, T	NA
53	PL-9	Philips-Advance	ICF-2S18-H1-LD	PS	2	18W*2	Series	C	C	C	C
54	PL-73	ESPEN	VE218120MR-1	PS	2	18W*2	Series	NA	NA	P, T	NA
55	PL-8	SUNPARK	U-218PS-W	PS	2	18W*2 ; 18W*1	Series	C	C	C	C
56	PL-11	Universal Lighting Technol	C218UNVME	PS	2	18W*2 ; 18W*1	Series	C	C	C	C
57	PL-21	Fulham	RHA-UNV-218-C	PS	2	18W*2 ; 18W*1	Series	C	C	C	C
58	PL-85	OSRAM SYLVANIA	QTP 1/2x18CF/UNV DM	RS	2	18W*2 ; 18W*1	Series	C	C	C	C
59	PL-89	Universal Lighting Technol	C218UNVBE	PS	2	18W*2 ; 18W*1	Series	C	C	C	C
60	PL-7	SUNPARK	LC 12010T	PS	1	13W*1	n. a	NA	NA	P, T	NA
61	PL-79	Philips-Advance	REB-113-M6-BLS	IS	1	13W*1	n. a	NA	NA	P, T	NA
62	PL-6	SUNPARK	U-213PS	PS	2	13W*2;13W*1	Series	NC	NC	NC	NC
63	PL-23	Philips-Advance	ICF-2S13-H1-LD	PS	2	13W*2;13W*1	Series	C	C	C	C
64	PL-24	Philips-Advance	ICF-2S13-M1-BS	PS	2	13W*2;13W*1	Series	C	C	C	C
65	PL-54	Universal Lighting Technol	C213UNVME	PS	2	13W*2;13W*1	Series	C	C	C	C
66	PL-74	Fulham	RHA-UNV-213-C	PS	2	13W*2;13W*1	Series	C	P	C	C
67	PL-78	Philips-Advance	ICF-2S13-H1-LD	PS	2	13W*2;13W*1	Series	C	C	C	C
68	PL-84	Philips-Advance	ICF-2S13-M1-BS-QS	RS	2	13W*2;13W*1	Series	C	C	C	C

Note: If lamp is driven by 13W or 18W ballast, the optical output can't reach the rated value.